

# BUZZSTOP-MKIII

Universal signal convertor & ground isolator



The Apart BUZZSTOP-MKIII is a universal input adaptor that can be used for all connections and extensions. The input level selector allows you to convert any amplifier output to any line-level output, balanced or unbalanced. (E.g.: You can convert a 100V loudspeaker signal into a balanced or unbalanced line level signal). The BUZZSTOP-MKIII also makes it possible to convert an unbalanced signal into balanced and vice versa.

A 19" adaptor set is available. This way it is possible to mount 2 BUZZSTOP-MKIII in a 19" rack. (REF: BUZZ-19)

Often the BUZZSTOP-MKIII is used to solve humm and buzz problems via the build-in audio transformer. This can be a perfect way to avoid ground loops.

## TECHNICAL SPECIFICATIONS

<b>inputs - line level - balanced</b>	Euroblock, 0dB-1V	<b>inputs - line level - unbalanced</b>	RCA cinch, 0dB-1V
<b>inputs - high level - PA amp</b>	Euroblock, 100V-70V-33V	<b>inputs - high level - low imp amp</b>	8 Ohm & 1kW-600W-120W
<b>inputs - high level - telephone</b>	Euroblock	<b>outputs - balanced</b>	Euroblock, Line 0dB-1V
<b>outputs - unbalanced</b>	RCA cinch, 0dB-1V	<b>width in mm</b>	241
<b>height in mm</b>	44	<b>depth in mm</b>	72
<b>weight in gr</b>	500		

MORE PICTURES

