

MICPAT-4

Selective 4-zone paging station



The Apart MICPAT-4 is a sturdy active multizone-paging microphone. It has a flexible gooseneck and a high-quality directional condenser microphone.

With MICPAT-4 you can make paging calls to a maximum of four zones simultaneously. It has been designed specifically for use with the Apart ZONE4 pre-amplifier and future models. Multiple MICPAT-4 mics can be connected in parallel by using the optional RJ45SPLIT splitter.

Operating this microphone is very straightforward: select the zones you want to page by pushing buttons 1 to 4. You can select all zones at once by pushing the 'all' button.

The call button is momentary: push to talk. All the other buttons are latching. During paging the call LED will light orange, and all other microphones connected in parallel will be temporarily disabled (busy). In a multi-microphone setup, the MICPAT-4 will automatically detect if another microphone is already paging. This is indicated by an orange call LED. When paging has ended, the LED will return to green.

MICPAT-4 and ZONE4 have an easy plug-and-play installation and comfortable, intuitive use. As all Apart products, they have been designed with installer ease in mind!

TECHNICAL SPECIFICATIONS

active	Yes	polar pattern	directional, low feedback, electret capsule
buttons	4 selection + Call + All Call	indicator	1 per button + multi color status
zones	4	frequency range	80 Hz - 20 kHz
nominal output level	2 V balanced	rated output impedance in ohms	50 balanced
power type	Phantom	mic stem length in mm	275
connector	RJ45	cable length in m	5
cable type	CAT5	width in mm	115
height in mm	60	depth in mm	162
weight in gr	550		

MORE PICTURES



ACCESSORIES



RJ45SPLIT

RJ45 Splitter : 1input, 4 output (MICPAT4 or ZONE4R)