

PM1122RL

Wall control panel with local input
for PM1122



The PM1122RL is a very affordable remote control panel with local audio input (mini-jack and XLR) for the PM1122, Apart's multifunctional pre-amplifier.

The control panel offers music level control, line source selection and microphone mix level control. The PM1122RL also adds a double local source input, which means that there can be a microphone on the XLR and/or an MP3 player, or a pc or other line input on the stereo mini-jack connector.

However, the local source input is always mono. There can be phantom power to the XLR connector by setting a jumper on the pack of the control panel.

The remote panels are connected to the PM1122 by a standard CAT-5 cable wired according to the T-568B protocol. The maximum wire length is up to 300m, according to circumstances. You can use one PM1122RL per zone. Mounting screws are included.

TECHNICAL SPECIFICATIONS

display	No	display backlight	No
supported main unit	PM1122	programmable functions	No
addressing	Hardwired	connector type	RJ45
max. cable length in m	300	power type	Phantom
inputs	Bal. Mic. & Unbal. Line	width in mm	115
height in mm	115	depth in mm	40
weight in gr	260		

MORE PICTURES



ACCESSORIES



BBI2

Universal BTicino built in box 2 x 3 modules



BB2

Build on box white for remote panel with input PM1122RL